



The steps of uploading the hex firmware by cura

PS: first of all , you need to prepare the hex firmware correspond to the printer type and put it in an easy place to find it , and turn on the printer , connect to PC via USB , pls make sure printer connect to correct serial port !


Step1: Open cura software , click “ file “ - “ machine settings “ - select correct “ serial port “




Step2: Click “ machine - install custom firmware “ on cura



Step3: Select the correct hex. file (firmware) , then click “ open “ in the pop-up interface



Step4: The firmware will be uploaded automatically and shows the progress bar , just need to wait for the progress bar is complete , then click “ OK “



Done !

Note:

If the uploading process appears error : timeout , please check if the printer driver program is installed correctly , or before uploading it has been selected on the corresponding driver serial port!

Please follow and repeat the above steps if timeout error !